


Current Equipment Type



B9A Base

TYPE 20D4 MINIATURE TRIODE-HEPTODE FREQUENCY CHANGER



The BRIMAR 20D4 is a triode-heptode frequency changer on the Noval (B9A) base, featuring very high conversion conductance.

RATINGS

Heater Voltage	6.3 volts
Heater Current	0.3 amp.
Heptode Anode Voltage	300 volts max.
Heptode Screen Voltage	125 volts max.
Triode Anode Voltage	150 volts max.
Total Cathode Current	17.5 mA max.

OPERATING CHARACTERISTICS

Heptode Anode Voltage	250 volts
Heptode Screen Voltage	100 volts
Heptode Control Grid (g_1) Voltage	-2 volts
Heptode Injection Grid (g_2) Voltage	0 volts
Anode Current	7.0 mA
Screen Grid Current	2.3 mA
Mutual Conductance (g_{1-a})	2.8 mA/V
Anode Impedance	0.9 Megohms
Control Grid Voltage for $g_m/100$	-20 volts
Triode Anode Voltage	100 volts
Triode Grid Voltage	0 volts
Anode Current	15 mA
Mutual Conductance	3.5 mA/V
Amplification Factor	16

OPERATION AS A FREQUENCY CHANGER

Heptode Anode Voltage	250 volts
Heptode Screen Voltage	100 volts
Heptode Control Grid Voltage	-2 volts
Triode Grid Resistor (g_t connected to g_3)	50 kilohms
Triode Grid Current	250 μ A
Conversion Conductance	850 μ A/V
Heptode Anode Current	3.0 mA
Heptode Screen Current	3.6 mA

INTER-ELECTRODE CAPACITANCES *

R.F. Input (g_{1h} -all)	4.5 pF
I.F. Output (a_h -all)	8.2 pF
Triode Input	2.1 pF
Triode Output	2.5 pF
Heptode Grid to Heptode Anode	0.01 pF

* Measured with external shield.