


MARCONI VALVES

TYPE DEH 410

Approximate Operating Data—Neglecting Resistance of Output Circuit.

Anode Volts	Grid Bias Volts
120-150	In Resistance Coupled Amplifier: -1½
50-150	As Grid Leak Detector: Connect grid leak to positive end of filament
75-150	As Anode Bend Detector: -1½ to -3
75-150	In High Frequency Amplifier: Positive, zero or negative according to method of stabilising or damping circuit.




Characteristic Curve of Average DEH 410 Valve.

TYPE DEL 410

Approximate Operating Data—Neglecting Resistance of Output Circuit.

Anode Volts	Grid Bias Volts
50-150	In High Frequency Amplifier: Positive, zero or negative according to method of stabilising or damping circuit.
50-150	As Grid Leak Detector: Connect grid leak to positive end of filament.
75-150	In Low Frequency Amplifier: -1½ to -4½



Characteristic Curve of Average DEL 410 Valve.

The valve in the purple box