

Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f . . . 6,3 V_a
 I_f . . . 0,33 A
 U_a . . . +6,3 V=
 U_{g1} . . . -0,45 V=
 I_a 1 mA
 S 2,6 mA/V
 μ 13
 R_i 5 k Ω

Prüfdaten:

Test operation:

Vérification:

U_f . . . 6,3 V \sim
 U_a . . . +10 V=
 U_{g1} 0 & -2 V=

In Stellung 13
auf Steuerwirkung

prüfen

In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

1026

Röhrenmeßgerät Modell W 19

MAX FUNKE, Adenau-Eifel 4. 56.


ECC 86

Triode + Triode
Karte 1025 + Karte 1026

Unbrauchbar
mauvais / Bad


?

G u t
Good / Bon

**Grenzdaten:**

Ratings: / Conditions maxima:

U_a . . . +30 V=
 I_k 20 mA
 R_k 20 k Ω
 R_{g1} 1 M Ω
 P_{Na} 0,6 W
 U_{fzk} . . . 30 V



5 mA