

Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f 2 V
 I_f 0,24 A
 U_a . . . +135 V=
 U_g 0
 I_a 2×5 mA
 R_{aa} 10 kΩ

Grenzdaten:

Ratings: / Conditions maxima:

U_a . . . +150 V=
 I_a 2×25 mA
 P 2,1 W
 = 2 Systeme

Prüfdaten:

Test operation:

Vérification:

U_f 2 V~
 U_a . . . +150 V=
 U_g . . . 0 & -2 V=

In Stellung 13
auf Steuerwirkung
prüfen

In position 13 is to
prove the control grid.
 En position 13 vérifier
l'action de commande de la
grille.

630

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 11, 54

1J6

1J6 G

1J6 GT

1J6 GX

19


Triode + Triode

Karte 630 + Karte 631


Unbrauchbar
mauvais / Bad

?

G u t
Good / Bon



10 mA



19

1J6

