

AR 4120 Tu		Type Herst.
4 1,2 ~		$U_f$ $I_f$ Heizart
NF-Verstärker Trafo/ Widers — —		Verw. Kbn-Lg. Kbn-Ø
200	200 <sup>1)</sup>	$U_a$
—	—	$U_{g3}$
—	—	$U_{g4}$
—	—	$U_{g3}$
—	—	$U_{g2}$
-1,5	-1,5	$U_{g1}$
1	0,2	$I_a$
—	—	$I_{g3}$
2,5	—	S
1	1	D
40	—	$R_i$
1,5	8	$R_b$
—	300	$R_a$
—	—	$R_{g3}$
—	—	$U_{g1} \sim$
—	80	V
—	—	$N_a \sim$
250	—	$U_b$ max
—	—	$U_{g2}$ max
1,5	—	$N_a$ max
—	—	$N_{g2}$ max
1	—	$R_{g1}$ max
1,5	—	$C_{g/a}$



AR 4120