

Type Herst.	DF 31 Va
U_f I_f Heizart	1,4 0,025 B
Verw. Kbn-Lg. Kbn-Ø	HF-Verstärker — —
U_a U_{g3} U_{g4} U_{g3} U_{g2} U_{g1}	120 — — 0 120 ¹⁶⁾ -4,5
I_a I_{g3}	— —
S D R_f	0,0065 — > 10000 ¹⁷⁾
R_k R_a R_{g3}	— — 120
$U_{g1} \sim$ V $N_a \sim$	— g = 600 —
U_b max U_{g3} max N_a max N_{g3} max R_{g1} max	135 135 0,2 0,1 3
$c_{g/a}$	0,006



DF 31