

Die gebräuchlichsten von Telefunken hergestellten Typen sind:

Type	Nutzleistung	Anodenspannung	Annäherungswerte**	
			Heizspannung	Heizstrom
RS 55	5 — 15 Watt	400 — 700 V.	10 Volt	3 Amp.
" 62	5 — 15 "	400 — 700 "	10 "	3 "
" 50	10 "	1000 "	10 "	1,5 "
" 69	20 "	800 "	10 "	3 "
" 67	15 — 25 "	800 — 1200 "	10 "	3 "
" 31	40 — 75 "	1000 — 1600 "	10 "	4 "
" 21	60 — 100 "	1500 — 2000 "	10 "	4 "
" 19	200 "	3000 "	14 "	4 "
" 32	500 "	6000 "	12 "	8 "
" 42	500 "	6000 "	16 "	8 "
" 18	500 "	3000 "	16 "	8 "
" 47	1 kW	10000 "	16 "	8 "
" 15	1,5 "	4000 "	16 "	16 "
" 53*	2,5 "	10000 "	16 "	16 "
" 53*	4 — 5 "	16000 — 20000 "	18 "	16 "

*) Für Fremderregung.

**) Die genauen Heizdaten (Fadenspannung in Volt) sind auf jeder Röhre vermerkt.

Abmessungen und Gewichte der Röhren mit Sockel:

Type	Gewicht	Höhe	Durchmesser
RS 55	200 g	200 mm	55 mm
" 62	200 "	150 "	55 "
" 10	200 "	200 "	55 "
" 69	200 "	200 "	55 "
" 67	200 "	200 "	55 "
" 31	250 "	215 "	60 "
" 21	250 "	215 "	60 "
" 19	250 "	265 "	60 "
" 32	600 "	390 "	95 "
" 42	600 "	390 "	95 "
" 18	600 "	390 "	95 "
" 47	750 "	400 "	140 "
" 15	1900 "	550 "	185 "
" 53	1900 "	550 "	185 "
" 54	2000 "	575 "	185 "