

**X 4122**  
 (Hexode)  
 für  
 Mischstufen


$V_f = 4 \text{ V}$   
 $I_f = 1 \text{ A}$   
 indirekt

$V_a = 200 \text{ V}$   
 $V_{g4} = -3 \text{ V}^{1)}$   
 $V_{g3} = 200 \text{ V}^{1)}$   
 $V_{g2} = 100 \text{ V}$   
 $V_{g1} = -1,5 \text{ V}$

$I_a = 4$   
 $I_{g3} = 10$   
 $I_{g2} = 1,5$

$S_c = 580 \mu\text{A/V}$   
 $R_i > 0,15 \text{ M}\Omega$

$W_a = 1 \text{ W}$   
 $W_{g3} = 2 \text{ W}$   
 $W_{g2} = 0,4 \text{ W}$   
 $I_k = 15 \text{ mA}$   
 $R_{g1} = 1 \text{ M}\Omega$   
 $V_{fk} = 20 \text{ V}$



<sup>1)</sup> g3 und g4: Oszillatorsystem