


<p><i>W 4080</i> (Triode) für NF. Verstärker</p>	<p>$V_f = 4 \text{ V}$ $I_f = 1 \text{ A}$ indirekt</p>	<p>Statische Daten: $V_a = 200 \text{ V}$ $V_g = -2,5 \text{ V}$</p>	<p>$I_a = 2,5$</p>	<p>$S = 1,3 \text{ mA/V}$ $\mu = 37$ $R_i = 28 \text{ k}\Omega$</p>	<p>$W_a = 1,5 \text{ W}$ $R_g = 1 \text{ M}\Omega$ $V_{fk} = 50 \text{ V}$</p>	
--	---	--	-------------------------------	--	---	---