


<p>X 2818 (Hexode) für Mischstufen</p>	<p>$V_f = 20 \text{ V}$ $I_f = 0,18 \text{ A}$ indirekt</p>	<p>$V_a = 200 \text{ V}$ $V_{g4} = -3 \text{ V}^{1)}$ $V_{g3} = 200 \text{ V}^{1)}$ $V_{g2} = 100 \text{ V}$ $V_{g1} = -1,5 \text{ V}$</p>	<p>$I_a = 3$ $I_{g3} = 7$ $I_{g2} = 1,8$</p>	<p>$S_c = 580 \mu\text{A/V}$ $R_i > 0,15 \text{ M}\Omega$</p>	<p>$W_a = 1 \text{ W}$ $W_{g3} = 2 \text{ W}$ $W_{g2} = 0,4 \text{ W}$ $I_k = 15 \text{ mA}$ $R_{g1} = 1 \text{ M}\Omega$ $V_{fk} = 100 \text{ V}$</p>	
		<p>¹⁾ g3 und g4: Oszillatorsystem</p>				