


X 4123 (Hexode) für regelbare HF- Verstärker	$V_f = 4 \text{ V}$ $I_f = 1,2 \text{ A}$ indirekt	$V_a = 200 \text{ V}$ $V_{\rho 4} = 80 \text{ V}$ $V_{\rho 2} = 80 \text{ V}$ $V_{\rho 3} = -2 \text{ V}$ $V_{\rho 1} = -2 \text{ V}$	$I_a = 3$ $I_{\rho 2 + \rho 4} = 3$	$C_{a\rho 1} < 0,002 \text{ pF}$	$W_a = 1 \text{ W}$ $W_{\rho 4} = 0,25 \text{ W}$ $W_{\rho 2} = 0,5 \text{ W}$ $I_k = 10 \text{ mA}$ $R_{\rho 1} = 3 \text{ M}\Omega$ $V_{fk} = 50 \text{ V}$	
		$V_{\rho 3} = -7 \text{ V}$ $V_{\rho 1} = -15 \text{ V}$		$S = 1,5 \text{ mA/V}$ $R_i = 0,5 \text{ M}\Omega$		