



# CK 6111

# Duotriode



Subminiatur B8D



$J_A$  - Bereich

$A_I$



100 V

$A_{II}$



100 V



30

## $J_A$ 13 mA

$U_{II}$

$G_{1II}$

$U_I$

$G_{1I}$



1 V

$K_I$

$K_{II}$

F

F

1 V

### Heizung 6,3 Volt

Meßkarte für NEUBERGER Röhrenmeßgeräte

#### Meßspannungen

Heizung	F	6,3	V
$U_I$	$G_{1I}$	1	-V
$U_{II}$	$G_{1II}$	1	-V
$U_{III}$			V
$U_{IV}$			V
A		100	V

#### Richtströme

$J_A$	13	mA
$J_{G_2}$		mA
S		mA/V